

HP LaserJet Enterprise M406dn (3PZ15A)



HP's entry-level Enterprise-class printer with speeds up to 42 ppm[9] and strongest security.[1]

HP's entry-level Enterprise-class printer with speeds up to 42 ppm[9] and strongest security.[1]



Easy to use, simple to manage

HP FutureSmart firmware can be updated with the latest features[2] to optimize your investment for years to come.

The world's most secure printing[1]

The operating code (BIOS) is automatically checked during startup and repairs itself if compromised.

Enhanced productivity to empower work teams

Give workgroups what they need to succeed with hundreds of HP and third-party solutions and card reader support.

Specifications

Print Resolution Technologies	300 dpi, 600 dpi, HP FastRes 1200, HP ProRes 1200
Print quality black (best)	Up to 1,200 x 1,200 dpi
Print speed black (ISO, A4)	Up to 38 ppm (default); Up to 40 ppm (HP high speed mode)
Print speed black (ISO, letter)	Up to 40 ppm (default); Up to 42 ppm (HP high speed mode)
Print speed	Up to 40 ppm (black)
Functions	Print
Duplex printing	Automatic (default)
Duty cycle (monthly, A4)	Up to 100,000 pages
Duty cycle (monthly, letter)	Up to 100,000 pages
Printer smart software features	Print preview, duplex printing, print multiple pages per sheet (2, 4, 6, 9, 16), collation, watermarks, store print jobs, easy-access USB
Energy savings feature technology	HP Auto-On/Auto-Off Technology; Instant-on Technology; Instant-on Copy
Replacement cartridges	AMS: For distribution and use in North America and Latin America only: HP 58A Black Original LaserJet Toner Cartridge (~3,000 pages) CF258A HP 58X High Yield Black Original LaserJet Toner Cartridge (~10,000 pages) CF258X EMEA: For distribution and use in Europe, Middle East, Russia, CIS, and Africa only: HP 59A Black Original LaserJet Toner Cartridge (~3,000 pages) CF259A HP 59X High Yield Black Original LaserJet Toner Cartridge (~10,000 pages) CF259X APJ: For distribution and use only in Asia Pacific - excluding China (PRC) and India: HP 76A Black Original LaserJet Toner Cartridge (~3,000 pages) CF276A HP 76X High Yield Black Original LaserJet Toner Cartridge (~10,000 pages) CF276X ^[5]
Supplies feature	HP JetIntelligence Cartridge
Connectivity, standard	1 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network
Connectivity, optional	HP Jetdirect LAN Accessory 8FP31A; HP Jetdirect 3100w BLE/NFC/Wireless Accessory 3JN69A
Network capabilities	Yes, via HP Jetdirect Ethernet embedded print server (standard) which supports: 10Base-T, 100Base-Tx, 1000Base-T; 802.3az (EEE) support on Fast Ethernet and Gig Links; IPsec (standard); 802.11a/b/g/n wireless networking (Optional); second Ethernet port (Optional).
Wireless capability	Optional, enabled with purchase of a wireless hardware accessory. Dual band Wireless Station and Wi-Fi Direct functionality available with HP Jetdirect 3100w BLE/NFC/Wireless Accessory 3JN69A
Mobile printing capability	HP ePrint; Apple AirPrint™; NFC touch-to-print (optional); Mopria™ Certified; Wi-Fi® Direct printing; ROAM capable for easy printing; PrinterOn Print
Network protocols, supported	Via built-in networking solution: TCP/IP, IPv4, IPv6; Print: TCP-IP port 9100 Direct Mode, LPD, Web Services Printing, IPP 2.0, Apple AirPrint™, HP ePrint; Discovery: SLP, Bonjour, Web Services Discovery; IP Config: IPv4 (BootP, DHCP, AutoIP, Manual), IPv6 (Stateless Link-Local and via Router, Statefull via DHCPv6); Management: SNMPv2/v3, HTTP/HTTPS, Syslog; Security: SNMPv3, SSL Cert Management, IPSec (IKEv1 and IKEv2), Firewall, 802.1x
Software included	No software solutions are included in the Box only on http://hp.com or http://123.hp.com
Compatible Operating Systems	Windows Client OS (32/64 bit)-, Win10, Win8.1, Win7 Ultimate, Mobile OS-, iOS, Android, Mac-, Apple® MacOS High Sierra v10.13, Apple® MacOS Mojave v10.14, Apple® MacOS Catalina v10.15, Discrete PCL6 Printer Driver-, For more information on the supported operating systems go to http://support.hp.com , Enter your product name and search, Click on User Guides and enter your product name and search for User Guide, Search for your (Product Name) - User Guide, Search for the Supported Operating Systems section, UPD PCL6 / PS Printer Drivers, Supported Operating systems, For more information on the supported operating systems see www.hp.com/go/upd
Sustainable impact specifications	Mercury-free
Energy star certified	Yes
Ecolabels	Blue Angel RAL-UZ 205; CECP; ENERGY STAR® certified; EPEAT® Silver
Blue Angel compliant	Yes, Blue Angel DE-UZ 205—only ensured when using Original HP supplies
Display area (imperial)	2.13 x 1.6 in
Display area (metric)	54 x 40.5 mm
Display	2.658" diagonal Color TFT-LCD back-lit (960 (H) x 240 (V))
Minimum dimensions (W x D x H)	381 x 357 x 220 mm
Minimum dimensions (W x D x H)	15 x 14 x 8.7 in
Weight	~8.5 kg (With Print Cartridges)
Weight	~18.7 lbs (With Print Cartridges)

Power consumption	531 watts (active printing), 8.1 watts (ready), 1.2 watts (sleep), 0.07 watts (auto-off/manual-on), 0.07 watts (manual off) <i>(Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.)</i>
Power supply type	Internal (built-in) Power Supply
What's in the box	HP LaserJet Enterprise M406dn printer; HP Black Original LaserJet Toner Cartridge (~3,000 pages); Getting started Guide; 1 Power cord ^[2]
Services (Care Pack)	U11X8E - HP 3y NBD LJ Ent M40x SVC; U11X9E - HP 4y NBD LJ Ent M40x SVC; U11XBE - HP 5y NBD LJ Ent M40x SVC; U11XCE - HP 3y 4h 9x5 LJ Ent M40x SVC; U11XDE - HP 4y 4h 9x5 LJ Ent M40x SVC; U11XFE - HP 5y 4h 9x5 LJ Ent M40x SVC; U11XGE - HP 3y 4h 13x5 LJ Ent M40x SVC; U11XHE - HP 4y 4h 13x5 LJ Ent M40x SVC; U11XJE - HP 5y 4h 13x5 LJ Ent M40x SVC; U11XKE - HP 3y NBD Onsite Exchange LJ Ent M40x SVC; U11XLE - HP 4y NBD Onsite Exchange LJ Ent M40x SVC; U11XME - HP 5y NBD Onsite Exchange LJ Ent M40x SVC; U11XNE - HP 3y ChnlPartsOnly LJ Ent M40x SVC; U11XQE - HP 4y ChnlPartsOnly LJ Ent M40x SVC; U11XRE - HP 5y ChnlPartsOnly LJ Ent M40x SVC; U11XSPE - HP 1y PW NBD LJ Ent M40x SVC; U11XTPE - HP 2y PW NBD LJ Ent M40x SVC; U11XVPE - HP 1y PW 4h 9x5 LJ Ent M40x SVC; U11XWPE - HP 2y PW 4h 9x5 LJ Ent M40x SVC; U11XXPE - HP 1y PW 4h 13x5 LJ Ent M40x SVC; U11XYPE - HP 2y PW 4h 13x5 LJ Ent M40x SVC; U11XZPE - HP 1y PW NBD Onsite Exch LJ Ent M40x SVC; U11Y0PE - HP 1y PW ChnlPartsOnly LJ Ent M40x SVC; U11XPPE - HP 2y PW ChnlPartsOnly LJ Ent M40x SVC; U9JT3E - HP Inst SVC w/nw Department Printer
Warranty	One-year, On-site Repair 24-hour / 7 day a week phone support

Top Recommended Displays, Accessories and Services

No Top Recommended Displays, Accessories and Services

Messaging Footnotes

[1] HP's most advanced embedded security features are available on HP Managed and Enterprise devices with HP FutureSmart firmware 4.5 or above. Claim based on HP review of 2019 published features of competitive in-class printers. Only HP offers a combination of security features to automatically detect, stop, and recover from attacks with a self-healing reboot, in alignment with NIST SP 800-193 guidelines for device cyber resiliency. For a list of compatible products, visit hp.com/go/PrintersThatProtect. For more information, visit hp.com/go/PrinterSecurityClaims

[2] Some features enabled by future HP FutureSmart firmware upgrades may not be available on older devices, if for example, physical product characteristics limit the functionality of the new feature.

[9] Measured using ISO/IEC 24734, excludes first set of test documents. For more information, see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

Technical Specifications Footnotes

[2] For yield information on the cartridge included with your printer, see <http://www.hp.com/go/toneryield>. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors.

[5] Declared yields based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/toneryield>

© Copyright 2021 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

