

## AURA-6800



Posiflex Aura-6800 series is an easy loading, low noise, high resolution, lightweight; high reliability and high performance thermal printer. Additionally, clearing a paper jam in the Posiflex Aura-6800 series printer is an easiest thing. The paper jams (in most cases) can be solving by push the "Hood Release Button" directly. This series of printers has been elegantly designed for Point-Of-Sale, kitchen & kiosk application. The Aura-6800 printer serve the stand-alone desktop application as well as the application within a Posiflex integrated POS system equally perfect.



- Paper jams can be solving by push the "Hood Release Button" directly
- Fast-speed printing (150mm per second).
- Supports application environment of Windows or OPOS or Linux.
- Low noise thermal printing.
- Drop-and-load structure for paper roll loading.
- Cash drawer control up to 2 cash drawers.
- Supports enhancement capability in kitchen bell for reminder function.
- Default with serial interface, option for parallel ,USB or LAN interface by plug in module.

### SPECIFICATION

Function	AURA-6800
Interface	Serial Port (RS-232), Parallel, Lan or USB.
Printing Method	Thermal dot line method
Printing Speed	150mm/sec
Paper Width	80mm
Maximum Printable Width	72mm (for 576 dots/line)
Default Printing Width	64mm (for 512 dots/line)
Paper Feed Method	Friction auto-feed
Paper Load Method	Drop and use
Auto-Cutter Type	Guillotine type
Auto-Cutter Capability	Partial cut (1 point at center left)
Manual cutter	Saw tooth blade
Indicators	Power: Green, Error: Red, Paper Out: Red.
Sensors	Hood Lock, Paper Near End, Paper Out, Overheat.

#### Language Support

International Character Set	15 international character sets supported (Denmark I , Denmark II , Ex-Jugoslavia, France, Germany, Italy, Japan, Korea, Latin America, Norway, Spain, Spain II , Sweden, UK, USA.
Character Code Page	23 code pages supported (Power on default code page can be set infactory by software program)
Bar Code Printing	UPC-A/E, EAN13/8, ITF, CODE39/93/128, CODABAR

#### Accessory

Paper Guide Adaptor	Optional 58 mm paper guide adaptor
Kitchen Bell	Optional
Wall mount kit	Optional

\*\* The product information and specifications are subject to change without prior notice.

20090723